DC200IF

Highly stabilized and precise fluxgate technology based current transducer, reengineered for cost sensitive, non-intrusive, isolated DC and AC current measurement applications up to 300A



Features

DANI

Linearity error maximum 6 ppm

Offset maximum 15 ppm

Fluxgate, closed loop compensated technology with fixed excitation frequency and second harmonic zero flux detection for enhanced accuracy and stability

Industry standard 6.3 x 0.8mm faston connection

Cost focused high performance current transducer

DC and AC current metering with +/-0.1% absolute accuracy up to 5kHz

Applications:

Gradient amplifiers for MRI devices

Precision power supplies, drives

Batteries testing and evaluation systems

Variable speed motor drives

Specification highlights	Symbol	Unit	Min	Тур.	Мах
Nominal primary AC current	IPN AC	Arms			200
Nominal primary DC current	IPN DC	A	-300		300
Measuring range	Îрм	A	-330		330
Primary / secondary ratio	n1 : n2		1:1000		1:1000
Linearity error	ε _L	ppm	-6		6
Offset current (including earth field)	I _{OE}	ppm	-15		15
DC-10Hz Overall accuracy @25°C (= \mathcal{E}_L + I_{OE})	acc8	ppm	-21		21
AC Maximum gain error from 10Hz to 5kHz	8G	%			±0.1
Operating temperature range	Ta	°C	-40		+85
Power supply voltages	Uc	V	±14.25		±15.75

Electrical specifications at Ta=23°C, supply voltage = ± 15V unless otherwise stated

Parameter		Symbol	Unit	Min	Тур.	Мах	Comment
Nominal primary AC cu	ırrent	I _{PN} AC	Arms			200	Refer to fig. 1 & 2 for derating
Nominal primary DC cu	urrent	I _{PN} DC	А	-300		300	Refer to fig. 1 for derating
Measuring range		I _{PM}	А	-330		330	Refer to fig. 1 & 2 for derating
Overload capacity		Î _{OL}	А			1000	Non-measured, 100ms
Nominal secondary cu	rrent	I _{SN}	mA	-300		300	At nominal primary DC current
Primary / secondary rat	io			1:1000		1:1000	
Measuring resistance		R _M	Ω	0		12	Refer to fig. 1 for details
-		εL	ppm	-6		6	ppm refers to nominal current
-	Linearity error		μΑ	-1,8		1,8	µA refers to secondary current
	Offset current		ppm	-15		15	ppm refers to nominal current
(including earth field)		I _{OE}	μA	-4,5		4,5	μA refers to secondary current
DC-10Hz Overall accur IOE)	acy@25°C (= &L +	acc£	ppm	-21		21	ppm refers to nominal DC current
Offset temperature		TCIOE	ppm/K	-2		2	ppm refers to nominal current
coefficient		ICIOE	μA/K	-0,6		0,6	µA refers to secondary current
Bandwidth		f(-3dB)	kHz	200			Small signal, graphs figure 3
Amplitude error	10Hz-5kHz					0,10%	
	5kHz-100kHz	٤G	%			2,00%	% refers to nominal current
	100kHz-200kHz					10,0%	
Phase shift	10Hz-5kHz		0			0.1°	
	5kHz -100kHz 100kHz - 1000kHz	θ	ů			0.5° 2.0°	
Response time to a ste		tr @ 90%	μs		1	2.0	di/dt = 100A/µs
Noise	0 - 100Hz	1 @ 90 %	μο		1	0,3	
	0 - 1kHz	noise	ppm rms			1,0	
	0 - 10kHz					5,0	Measured on secondary current
	0 - 100kHz					20,0	
Fluxgate excitation freq		f _{Exc}	kHz		15,6		
Induced rms voltage or	n primary conductor		μV rms			5	
Power supply voltages		Uc	V	±14.25		±15.75	
Positive current consumption		lps	mA			35	Add Is (if Is is positive)
Negative current consumption		Ins	mA			35	Add Is (if Is is negative)
Operating temperature range		Та	C	-40		85	
Stability							
Offset stability over time			ppm /	-10		10	ppm refers to nominal current
			month	-3		3	μA refers to secondary current
Impact of external magnetic field				-15		15	ppm refers to nominal current
			ppm / mT	-4,5		4,5	µA refers to secondary current

Measurement resistor RM and ambient temperature derating (Fig. 1)

Maximum external resistance vs. ambient temperatures 40 Maximum measurement resistor 35 30 25 20 Value (Ohm) 15 10 5 0 220 240 260 280 300 320 340 200 Primary Current, DC or peak (A) – R_max_55 R_max_70 R_max_25 • R_max_40

Frequency and ambient temperature derating (Fig. 2)

Max current (Arms) 85 deg Max current (Arms) 65 deg Max current (Arms) 45 deg

Maximum primary current Arms

Frequency characteristics (Fig. 3)



DANI/ENSE

Precision – Innovation www.danisense.com



Isolation specifications

Parameter	Unit	Value
Clearance	mm	9
Creepage distance	mm	10
Comparative tracking index (CTI)	V	> 600
Rms voltage for AC isolation test, 50/60 Hz, 1 min - Between primary and (secondary and shield (GND))	kV	5.7
Impulse withstand voltage (1.2/50µs)	kV	10.4
Rated rms isolation voltage reinforced isolation, overvoltage category III, Pollution degree 2 according to IEC 61010-1 and EN50780	V	300 600

Absolute maximum ratings

Parameter	Unit	Max	Comment
Primary	kA	1.5	Maximum 100ms
Power supply	V	±16.5	

Environmental and mechanical characteristics

Parameter	Unit	Min	Тур	Max	Comment
Operating temperature range	°C	-40		85	
Storage temperature range	°C	-40		85	
Relative humidity	%	20		80	Non-condensing
Mass	kg		0.250		
Connections	4 Industrial faston 6.3 x 0.8mm				
Standards	EN 61326-1 EMC				











(general tolerance 0.3mm unless otherwise stated)

DC200IF connection



Positive current direction

Is identified by an arrow on the transducer label

CAUTIONS:

- PLEASE IMPERATIVELY RESPECT <u>CONNECTION POLARITIES</u> TO PREVENT DESTRUCTION OF THE TRANSDUCER
- PLEASE ENSURE <u>ADEQUATE CURRENT AND VOLTAGE RATING</u> <u>OF POWER SUPPLES</u> TO AVOID SATURATION

Mounting instructions

- Base plate mounting
- Side mounting

2 holes φ5.5 2 holes φ5.5